POWER SUPPLY COMPATIBILITY MATRIX FOR WIREFREE

Please refer to product instructions for more detailed information.
NC = Not Compatible or not tested

⚠ Motors listed below are intended whatever the radio technology RTS / ZigBee

MOTOR COMPATIBILITY WITH POWER SOURCES

	Input 12VDC					Input 120-230VAC ~ 50Hz/60Hz		
	External Li-ion Battery Pack	**WF Li-ion Solar Panel**	**External Li-ion 2 Batt. Pack**	**Integrated External Li-ion 2 Batt. Pack**	**Li-ion 2 Solar Panel**	**Power supply for Wirefree**	**Li-ion Charger plug**	**Li-ion 2 Power unit / Pro charging hub**
	9021217	**9025293**	**9028930**	**9029224**	**9029114**	**1822445 9028893 9029070 1870940 (1)**	**9021027 9021028 9025165 9025166 (1) 9027545 9026942 9027597 9027682 9028547 9028548**	**9028920 9028921 9028922 9028923 (1) 9028924 9028925 9028926 9028927 9028928 9028929 9028978 9028979**
SHAFT MOTORS								
Cord Lift 32	OK	Only with the External Li-ion Battery Pack (9021217)	OK	NC	Only with Li-ion 2 Batt. Pack (9028930, 9029224)	OK	Only with the External Li-ion Battery Pack (9021217)	Only with Li-ion 2 Batt. Pack (9028930, 9029224)
Roll Up JR 30 WF	OK		OK	NC		OK		
Tilt & Lift 25 WF	OK		OK	OK		OK		
Tilt Only 50 WF	OK		OK	OK		OK		
TDBU 25 WF	NC		OK	OK		OK		
TDBU 45 WF	NC		OK	OK		OK		
GENERATION 1 MOTORS								
Roll Up 28 WF / Altus 28 WF	OK	Only with the External Li-ion Battery Pack (9021217)	OK	NC	Only with the External Li-ion 2 Batt. Pack (9028930)	OK	Only with the External Li-ion Battery Pack (9021217)	Only with the External Li-ion 2 Batt. Pack (9028930)
Roll Up 28 WF II / Altus 28 WF II	OK		OK	NC		OK		
Sonesse 28 WF	OK		OK	NC		OK		
Roll Up 24 WF Li-ion	NC	OK	NC	NC	NC	NC	OK	NC
Roll Up 28 WF Li-ion II / Altus 28 WF Li-ion II	NC	OK	NC	NC	NC	NC	OK	NC
Roll Up Basic 28 WF Li-ion II / Altus Basic 28 WF Li-ion II	NC	OK	NC	NC	NC	NC	OK	NC
Sonesse 28 WF Li-ion	NC	OK	NC	NC	NC	NC	OK	NC
Sonesse Ultra 30 WF Li-ion	NC	OK	NC	NC	NC	NC	OK	NC
Sonesse 40 WF Li-ion	NC	OK	NC	NC	NC	NC	OK	NC
GENERATION 2 MOTORS								
Roll Up2 24 WF Li-ion	NC	NC	NC	NC	OK	NC	NC	OK
Sonesse2 28 WF	OK	Only with 9021217	OK	NC	Only with 9028930	OK	Only with 9021217	Only with 9028930
Sonesse2 Basic 28 WF Li-ion	NC	NC	NC	NC	OK	NC	NC	OK
Sonesse2 28 WF Li-ion	NC	NC	NC	NC	OK	NC	NC	OK
Sonesse2 Ultra 30 WF Li-ion	NC	NC	NC	NC	OK	NC	NC	OK
Sonesse2 40 WF Li-ion	NC	NC	NC	NC	OK	NC	NC	OK
Movelite WireFree 35	NC	NC	NC	NC	NC	NC	NC	From index TBC
Irismo Plus WireFree 35	NC	NC	NC	NC	NC	NC	NC	From index TBC
Glydea2 ULTRA 50 WF Zigbee	NC	NC	NC	NC	NC	NC	NC	OK

(1) Mandatory for cULus certified products.

Copyright © Somfy Activités SA. All rights reserved
SOMFY ACTIVITY SA, Société Anonyme, capital 35.000.000 Euros, RCS Annecy, 303.970.230 - 01/2025

POWER SUPPLY COMPATIBILITY MATRIX FOR WIREFREE

DC POWER SOURCES - EXTERNAL BATTERIES COMPATIBILITY

		Ref: 9021217 External Li-ion Battery Pack	Ref: 9028930 External Li-ion 2 Batt. Pack	Ref: 9029224 Integrated External Li-ion 2 Batt. Pack	Ref: 9029424 LI-ION 2 BATTERY-6
Input 120-230VAC ~ 50Hz/60Hz					
9021027 / 9021028 /9025165 / 9025166 / 9027545 / 9026942 / 9027597 / 9027682 / 9028547 / 9028548	Li-ion Charger plug	OK	NC	NC	NC
9028920 / 9028921 / 9028922 / 9028923 / 9028924 / 9028925 / 9028926 / 9028927 / 9028928 / 9028929	Li-ion 2 charger	NC	OK	OK	OK
9028978 / 9028979	16 Ports Charging Station	NC	OK	OK	OK
1822445 / 9028893 / 9029070 / 1870940	Power supply for Wirefree	NC	NC	NC	NC
Input 12VDC					
9025293	WF Li-ion Solar Panel	OK	NC	NC	NC
9029114	Li-ion 2 Solar Panel	NC	OK	OK	NC

BATTERIES SPARE PARTS FOR LI-ION MOTORS

Range	Model	Reference	Compatible motors
Range 24	LI-ION BATTERY PACK DIAM 24	9027606	Roll Up 24 WF Li-ion / Roll Up2 24 WF Li-ion
Range 28	LI-ION BATTERY PACK DIAM 28	9021015	Roll Up 28 WF Li-ion / Altus 28 WF Li-ion Roll Up 28 WF Li-ion II / Altus 28 WF Li-ion II Sonesse 28 WF Li-ion / Sonesse2 28 WF Li-ion
	LI-ION BATTERY PACK BASIC 28	9027607	Roll Up Basic 28 WF Li-ion / Altus Basic 28 WF Li-ion Roll Up Basic 28 WF Li-ion II / Altus Basic 28 WF Li-ion II
	LI-ION 2 BATT PACK BASIC 28 3C	9029607	Sonesse2 Basic 28 WF Li-ion ⚠ HP versions only
	LI-ION 2 BATT PACK BASIC 28 2C	9029606	Sonesse2 Basic 28 WF Li-ion ⚠ Standard versions only
Range 30	LI-ION BATTERY PACK DIAM 30	9027610	Sonesse 30 WF Li-ion Sonesse Ultra 30 WF Li-ion / Sonesse2 Ultra 30 WF Li-ion
Range 40	LI-ION BATTERY PACK DIAM 40	9027608	Sonesse 40 WF Li-ion / Sonesse2 40 WF Li-ion

SAFETY INFORMATION - LIST OF WARNINGS

The battery type reference is indicated in the table hereabove.
The method to remove, insert and replace the batteries is described in the instructions.
Exhausted batteries are to be removed from the appliance and safely disposed of.
Separate batteries from other types of waste and recycle them via your local collection facility.
If the device is to be stored unused for a long period, the batteries should be removed.
The supply terminals are not to be short-circuited.
Not respecting above warnings may result in an unsafe use of the batteries.

5158703B

Copyright © Somfy Activités SA. All rights reserved
SOMFY ACTIVITY SA, Société Anonyme, capital 35.000.000 Euros, RCS Annecy, 303.970.230 - 01/2025